

NORDIC MARKET EXPERT GROUP

NORDIC EDIEL CODE LIST LIBRARY

Version: Version 1.5,L
Date: October 15th, 2020

CONTENT

1	INTRODUCTION	3
1.1	REFERENCES.....	3
1.2	CHANGE LOG.....	3
2	NORDIC EXTENSIONS TO ENTSO-E CODE LISTS	7
2.1	ASSET TYPE CODE	7
2.2	BUSINESS TYPE CODE	8
2.3	DOCUMENT TYPE CODE	13
2.4	OBJECT AGGREGATION CODE.....	15
2.5	PRICE CATEGORY TYPE CODE.....	16
2.6	PROCESS TYPE CODE	17
2.7	REASON CODE	18
2.8	ROLE CODE.....	20
3	NORDIC CODES USED IN NORDIC DOCUMENTS	21
3.1	BID TYPE CODE.....	21
3.2	TYPE OF AREA CODE	22
3.3	PRODUCTION TYPE CODE	23
3.4	PRODUCTION UNIT TYPE CODE	24
3.5	MGA TYPE CODE	25
3.6	SETTLEMENT METHOD CODE	26

1 Introduction

The *Nordic Ediel Code List Library* shows codes maintained by the Nordic Market Expert Group (NMEG), used in the Nordic energy market.

NMEG seeks to use codes from international standardisation bodies, such as ENTSO-E, ebIX[®] and UN/CEFACT. When the need for a new code turns up and there is no available code issued by a relevant body, NEG will issue a Nordic code, normally having three 3 letters and/or digits, starting with the letter Z. Normally NEG will send a Maintenance Request (MR) asking for a new code from one of the relevant international standardisation bodies. In special circumstances the NEG Znn code may be permanent.

The following code prefixes are normally used:

Ann	ENTSO-E codes
Bnn	ENTSO-E codes
Cnn	ENTSO-E codes
Enn	ebIX [®] codes
Nnn	NorNed codes
xxx	UN/CEFACT codes
Znn	Nordic codes

Where:

n = number

x = number or character

1.1 References

- [1] ENTSO-E code list, see <https://www.entsoe.eu/publications/electronic-data-interchange-ediel-library>
- [2] UN/CEFACT Code lists (UNCL), see <http://www.unece.org/trade/untdid/welcome.htm>
- [3] ebIX code list, see <http://www.ebix.org/>
- [4] Nordic code list, see <http://www.ediel.org/>

1.2 Change log

Ver/rel/rev	Changed by	Date	Changes
1.5.L	Ove Nesvik	20201015	<p>«deprecated» codes that have got a new official ENTSO-E code:</p> <ul style="list-style-type: none"> • Role type: Z05 Trader -> A47 Energy Trader • Business Types: Z02 Frequency bias -> C25 Frequency bias Z03 Frequency Containment Reserves, Normal (FCR-N) -> C26 Frequency Containment Reserves, Normal (FCR-N) Z06 Frequency Containment Reserves, Disturbance (FCR-D) -> C27 Frequency Containment Reserves, Disturbance (FCR-D) Z52 Small scale production -> C29 Small scale production Z32 System price -> C30 System price

			<ul style="list-style-type: none"> Process type: Z05 Bilateral trade -> A59 Internal trade reporting Z04 Reserve option market -> A58 Reserve option market
1.5.K	Ove Nesvik	20200921	<ul style="list-style-type: none"> The following Asset Type Codes are no longer «deprecated»: Z04 Thermal Z05 Wind The following code Asset Type Code is added: Z08 wave
1.5.J	Ove Nesvik	20200818	<ul style="list-style-type: none"> New Business Type: Z95 Non-conform load schedule Z96 Conform load schedule Updated the definition of Reason code Z35 New Reason codes: Z53 FRR-M, System Regulation Z54 Activation by AOF (Activation Optimisation Function) Z55 Manual activation not based on AOF
1.5.I	Ove Nesvik	20200723	<ul style="list-style-type: none"> New Business Type: Z94 Frequency Containment Reserve-Disturbance (FCR-D), one-step activation
1.5.H	Ove Nesvik	20200706	<ul style="list-style-type: none"> Deprecation of codes approved by ENTSO-E. Reneme of Process Type Z13 from “ACE OL Report” to “Corrected real time values”.
1.5.G	Ove Nesvik	20200604	<ul style="list-style-type: none"> Addition of Reason Codes: Z50 Supportive power special Z51 Supportive power disturbance Z52 Transit SB Loop Short
1.5.F	Ove Nesvik	20200527	<ul style="list-style-type: none"> Addition of Business Types: Z90 Power Plan Trade Z91 Loop transit Z92 Agreed supportive power (ASP) Z93 Production adjustments
1.5.E	Ove Nesvik	20200416	<ul style="list-style-type: none"> Addition of Business Types: Z88 Total planned flow Z89 Expected countertrade Addition of Object aggregation code: Z02 Mutually Regulated Areas (MRA)
1.5.D	Ove Nesvik	20200309	<ul style="list-style-type: none"> Addition of Business Types: Z77 ACE OL Z84 Inertia Z85 FFR process Z86 Frequency nadir Z87 Reference incident Addition of Document Types: Z35 ACE OL Z36 Power Prognoses Addition of Process Type: Z14 Fast Frequency Reserve (FFR) Process

			<ul style="list-style-type: none"> • Addition of Reason Codes Z42 to Z49 • Deprecated a set of codes where new codes have been issued by ENTSO-E CIM EG.
1.5.C	Ove Nesvik	20191016	<ul style="list-style-type: none"> • Addition of Settlement method code: <ul style="list-style-type: none"> Z01 Flex settled • Deprecated a set of codes where new codes have been issued by ENTSO-E CIM EG. • Addition of Document Type: <ul style="list-style-type: none"> Z34 Market Operator Configuration Document
1.5.B	Ove Nesvik	20190111	<ul style="list-style-type: none"> • Deprecated codes that no longer are used • Addition of definition for Document Type Z16 • Addition of Document Types Z24 to Z33 • Addition of Process Types Z08 to Z11 • Addition of Reason Codes Z40 to Z41 • Addition of Role Code Z06
1.5.A	Ove Nesvik	20180425	<ul style="list-style-type: none"> • Addition of Trade Structure Document Types: <ul style="list-style-type: none"> Z24 Request Bilateral Trade Structure Document Z25 Request PX Trade Structure Document Z26 Bilateral trade structure master data document containing master data changed within the Validity Time Interval Z27 Bilateral trade structure master data document containing all valid master data within the Validity Time Interval Z28 PX trade structure master data document containing master data changed within the Validity Time Interval Z29 PX trade structure master data document containing all valid master data within the Validity Time Interval
1.4.B	Ove Nesvik	20170419	<ul style="list-style-type: none"> • Rename of Document Type codes: <ul style="list-style-type: none"> Z12 Request change of retailer consumption master data Z13 Request change of Resource Object master data Z18 Party Relation Master Data Document containing master data changed within the Validity Time Interval Z19 Party Relation Master Data Document containing all valid master data within the Validity Time Interval • Rename of Document Type codes to: <ul style="list-style-type: none"> Z20 Retailer consumption master data document containing master data changed within the Validity Time Interval Z21 Retailer consumption master data document containing all valid master data within the Validity Time Interval Z22 Resource Object master data document

			<p>containing master data changed within the Validity Time Interval</p> <p>Z23 Resource Object master data document containing all valid master data within the Validity Time Interval</p>
1.4.A	Ove Nesvik	20170419	<ul style="list-style-type: none"> • Addition of Price category type codes: <ul style="list-style-type: none"> Z01 Buying Z02 Selling Z03 Average • Added Document Type Codes Z20, Z21, Z22 and Z23 • Rephrased Document Type Codes Z12 and Z13 • Updated logos on the front page <p>Removed NPS</p>
1.3.H	Ove Nesvik	20170213	<p>Textual corrections:</p> <ul style="list-style-type: none"> • Updated logos on the front page <p>Updated NTC and NEG member list</p>
1.3.G	Ove Nesvik	20161121	<p>Added Document Types:</p> <p>Z18 Party Relation Master Data Document where Validity Start and/or Validity End are within the Validity Period”</p> <p>Z19 Party Relation Master Data Document where relations are valid sometime within the Validity Period”</p>
1.3.F	Ove Nesvik	20160629	<p>Addition of Document type Z17 Spot Market Bid Status Report</p>
1.3.E	Ove Nesvik	20160525	<p>Addition of Z99 Sub-Grid Area</p>
1.3.D	Ove Nesvik	20150904	<p>MGA type “Z02 Only losses” is deprecated</p>
1.3.C	Ove Nesvik	20150623	<p>Addition of Business type Z68 Production Unit own consumption</p>
1.3.B	Ove Nesvik	20150519	<p>Rename of Production Unit Type code to Production Type code</p>
1.3.A	Ove Nesvik	20150503	<p>Addition of Production unit type code and the codes</p> <p>Z01 Normal</p> <p>Z02 Minor</p>
1.2.A	Ove Nesvik	20150421	<p>Addition of MGA Type:</p> <p>Z07 Transmission (main/central) grid</p>
Draft 1.2.A	Ove Nesvik	20150130	<p>Addition of Asset Type:</p> <p>Z07 Consumption”</p> <p>Addition of Object aggregation:</p> <p>Z01 Generator group</p>
Draft 1.2.A	Ove Nesvik	20141001	<p>Addition of Reason codes Z29-Z39</p>
Draft 1.2.A	Ove Nesvik	20140717	<p>Deprecation of Business Type Codes:</p> <p>Z53 (B14) Production deviation</p> <p>Z54 (B15) Consumption deviation</p> <p>Z55 (B20) Balance up regulation price</p> <p>Z56 (B21) Balance down regulation price</p> <p>Z57 (B22) Main direction</p> <p>Z58 (B23) Consumption imbalance price</p> <p>Z59 (B24) Production sales imbalance price</p> <p>Z60 (B25) Production purchase imbalance price</p> <p>Z61 (B26) Average balance price between MBAs</p> <p>Z62 (B27) Pumped</p> <p>Z63 (B28) Large installation consumption</p>

			Z65 (B29) MGA imbalance
1.1.A	Ove Nesvik	20140422	Addition of Business Type codes: Z55 Balance up regulation price Z56 Balance down regulation price Z57 Main direction Z58 Consumption imbalance price Z59 Production sales imbalance price Z60 Production purchase imbalance price Z61 Middle balance price between MBAs Z62 Pumped Z63 Large installation consumption Z64 Internal trade difference Z65 MGA imbalance Addition of Document Type codes: Z10 Connected Metering Grid Area (MGA) document Z11 Market Balance Area (MBA) structure document Addition of new code list, Type of Area code: Z01 Market Balance Area (MBA) Z02 Metering Grid Area (MGA)
1.0.B	Ove Nesvik	20140207	Addition of Bid Type Code: Z04 Profile block bid Addition of Business Type Codes: Z53 Production deviation Z54 Consumption deviation
1.0.A	Ove Nesvik	20131212	First approved version

2 Nordic extensions to ENTSO-E code lists

2.1 Asset type code

	Name	Description
Z01		Deprecated (use A08 Busbar instead)
Z02		Deprecated (not used anymore)
Z03	Transformer station	A resource that can transform voltage
Z04	Thermal	A resource using Thermal for energy
Z05	Wind	A resource using Wind for energy
Z06		Deprecated (Use “ B10 Hydro Pumped Storage”, “ B11 Hydro Run-of-river and pondage” or “ B12 Hydro Water Reservoir” instead)
Z07		Deprecated (Use “ A05 Load” instead)
Z08	Wave	A resource using wave for energy

2.2 Business type code

	Name	Description
N03	In-feed ATC	Available transfer capacity at the in-feed side of a tie-line or cable (i.e. into the cable, out from sending area) (E.g. used in the NorNed project)
N04	Out-feed ATC	Available transfer capacity at the out-feed side of a tieline or cable, i.e. after subtraction of grid loss. (i.e. out of the cable, into receiving area) (E.g. used in the NorNed project)
Z01		Deprecated (Use A77 , <i>Production, dispatchable</i> instead)
Z02		Deprecated (Use C25 , <i>Frequency bias</i> instead)
Z03		Deprecated (Use C26 , <i>Frequency Containment Reserve-Normal (FCR-N)</i> instead)
Z04		Deprecated (Use A78 , <i>Consumption, dispatchable</i> instead)
Z05	Net internal trade counterpart	Net internal trade as reported from the counterpart, used during matching procedure.
Z06		Deprecated (Use C27 , <i>Frequency Containment Reserve-Disturbance (FCR-D)</i> instead)
Z07		Deprecated (Use A70 , <i>Production, unavailable</i> instead)
Z08	Trade, unconfirmed	The trade plan of an actor when not matched against a counterpart, used during matching procedure.
Z09		Deprecated (Use A89 , <i>Spinning reserve</i> (The extra generating capacity that is available by increasing the production of generators that are already connected to the power system))
Z10		Deprecated (Use A10 , <i>tertiary reserves</i>)
Z11		Deprecated (Use A12 , <i>Secondary control (A time series concerning secondary reserve)</i>)
Z12	Total primary reserve	Sum of all primary reserves
Z13	Balance regulation activations	Activations of tertiary reserves in the Balance regulation market
Z14	System operator adjustment	Proposed adjustment by the <i>System operator</i> , used during matching procedure.
Z15	Result of an automatic System operator adjustment	Forced adjustment by the <i>System operator</i> , used during matching procedure.
Z16	Market schedules difference	Difference between own and counterparty market schedules, used during matching procedure.
Z17	Technical minimum	Technical minimum possible, under minimum, Resource Object having the possibility of using overload areas.
Z18	Technical maximum	Technical maximum possible, maximum incl. overload, Resource Object having the possibility of using overload areas.
Z19	Total maximum production	Schedule for maximum total production.
Z20	Total minimum production	Schedule for minimum total production.

Z21	Total Transfer Capacity (TTC)	The <i>Total Transfer Capacity</i> is the maximum exchange program between two areas compatible with operational security standards applicable at each system if future network conditions, generation and load patterns were perfectly known in advance.
Z22	Maximum production capacity	Maximum total value of planned production.
Z23	Minimum production capacity	Minimum total value of planned production
Z24	Peak load resource	Peak load resource refers to power plants which produce electricity using condensing power capacity covered by the power load reserve arrangement and may also refer to disconnectable consumption.
Z25		Deprecated Use A66 , <i>Energy flow</i> , together with an object aggregation element
Z26		Deprecated Use A23 , <i>Balance management</i>
Z27	Operational capacity (OC)	<i>Operational capacity</i> is exchanged between <i>System operators</i> . The OC is the available transfer capacity as established during the operational day, i.e. the capacity available after closure of the intra-day market. The OC is used for system operation and not for market purposes. The OC may be both higher and lower than the ATC. The OC may be negative. <i>This is a permanent Nordic code.</i>
Z28	Balance regulation power	Offered tertiary reserves to the Balance regulation market
Z29	Reserves option power	Offered tertiary reserves to the Reserves option market
Z30		Deprecated i.e. not used
Z31		Deprecated (Use A79 , <i>Production, non-dispatchable</i> instead)
Z32		Deprecated (Use C30 <i>System price</i> instead)
Z33		Deprecated (this information should be found as <i>Process type</i> at the header level)
Z34		Deprecated (this information should be found as <i>Process type</i> at the header level)
Z35	Commercial bid	The time series provides commercial bids.
Z36	Reserve bid	The time series provides reserve bids.
Z37	Primary reserves activations	Activations of primary reserves
Z38	Hydro production	The business being described concerns production based on hydro power
Z39	Nuclear production	The business being described concerns production based on nuclear power
Z40	Thermal production	The business being described concerns production based on thermal power
Z41	Wind production	The business being described concerns production based on wind power
Z42	Decentralised production	The business being described concerns production based on decentralised power
Z43	Gas turbine and diesel production	The business being described concerns production based on gas turbine and diesel power
Z44	Other thermal production	The business being described concerns production based on other thermal power

Z45	Disturbance on the Link	Nordic code (currently used by SwePol)
Z46	System Operator redispatching, in case of ASP special	Nordic code (currently used by SwePol)
Z47	Loop Flow	Nordic code (currently used by SwePol)
Z48	Number of return cables	Nordic code (currently used by SwePol)
Z49		Deprecated
Z50	Commercial wind production	The time series provides commercial bids based on wind production
Z51		Deprecated
Z52		Deprecated (Use C29 <i>Small scale production</i>)
Z53		Deprecated (Use B14 instead)
Z54		Deprecated (Use B15 instead)
Z55		Deprecated (Use B20 instead)
Z56		Deprecated (Use B21 instead)
Z57		Deprecated (Use B22 instead)
Z58		Deprecated (Use B23 instead)
Z59		Deprecated (Use B24 instead)
Z60		Deprecated (Use B25 instead)
Z61		Deprecated (Use B26 instead)
Z62		Deprecated (Use B27 instead)
Z63		Deprecated (Use B28 instead)
Z64	Internal trade difference	A time series concerning internal trade difference, within a Market balance area, i.e. the difference between trades reported from an out party (seller) and an in party (buyer). The internal trade difference is the delta value between what is reported by the two Balance responsible Parties.
Z65		Deprecated (Use B29 instead)
Z66	Last resort	A time series concerning consumption handled by supplier of last resort
Z67	TRM	Transmission Reliability Margin
Z68	Production Units own consumption	The consumption of one or more Production Units
Z69	Metered frequency	A time series concerning metered frequency
Z70		Deprecated (use " C17 Market price and total volume" instead)
Z71		Deprecated (use " C18 Import price" instead)
Z72		Deprecated (use " C19 Capacity allocated (excluding price)" instead)

Z73	Fast active disturbance reserve	The fast active disturbance reserve is the manual reserve (FRR-M) available within 15 minutes in the event of the loss of an individual principal component (production unit, line, transformer, bus bar etc.). Restores the <i>frequency controlled disturbance reserve</i> .
Z74	Imbalance sales price	A time series concerning imbalance prices for sales
Z75	Imbalance purchase price	A time series concerning imbalance prices for purchase
Z76	Day ahead prices used for CZC forecast calculation	20190403: Reserved by Statnett (Stein-Ole)
Z77	ACE OL (Area Control Error Open Loop)	The Area Control Error Open Loop (ACE OL) is the real-time imbalance of an area in the power system without automatic Frequency Restoration Reserve (aFRR) and manual Frequency Restoration Reserves (mFRR). ACE OL is the imbalance before any operator balancing actions.
Z78	Upper Alert	A time series concerning the upper limit before an alarm is raised
Z79	Upper Emergency	A time series concerning the upper limit before an emergency is raised
Z80	Lower Alert	A time series concerning the lower limit before an alarm is raised
Z81	Lower Emergency	A time series concerning the lower limit before an emergency is raised
Z82	Upper Warning	A time series concerning the upper limit before a warning is raised
Z83	Lower Warning	A time series concerning the lower limit before a warning is raised
Z84	Inertia	A time series concerning the ability of the kinetic energy stored in the rotating masses in the electricity system to resist changes in frequency.
Z85	FFR	A time series concerning the Fast Frequency Reserve (FFR), a power response activated within about one second when the system frequency drops below a certain level.
Z86	Frequency nadir	A time series concerning the expected lowest value of the frequency, after a disturbance.
Z87	Reference incident	A time series concerning the expected maximum incident size in MW.
Z88	Total planned flow	A time series concerning total planned flow of power between areas.
Z89	Expected countertrade	The planned supportive power corrections.
Z90	Power Plan Trade	Sum of planned flow considering the Day ahead and Intraday market.
Z91	Loop transit	Flow resulting from agreed loop flows and transit agreement.
Z92	Agreed supportive power (ASP)	Flow from agreed supportive power.
Z93	Production adjustments	Period shift products activated in the balancing time frame where the activation and need are in different areas.
Z94	Frequency Containment Reserve-Disturbance (FCR-D), one-step activation	FCR-D one step activation, is a reserve that is automatically activated when the frequency falls below 49.90 Hz after an imbalance, activated in one step, as opposed to a linear activation.
Z95	Non-conform load schedule	Non-Conform Load Schedule: Loads that do not follow a daily and seasonal load variation pattern.

Z96	Conform load schedule	Conform Load Schedule: A curve of load versus time (X-axis) showing the active power values (Y1-axis) and reactive power (Y2-axis) for each unit of the period covered. This curve represents a typical pattern of load over the time period for a given day type and season.
------------	-----------------------	-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

2.3 Document type code

	Name	Description
Z01		Deprecated (Use A14 , <i>Resource Provider Resource Schedule (Operational schedule)</i>)
Z02		Deprecated (Use A04 , <i>System Operator area schedule</i> instead)
Z03	Auction Specification Document	The document provides auction specification information.
Z04	Operational schedule, binding	The document provides binding operational (resource) schedules from the System operator, after market cut-off time.
Z05		Deprecated (use “ B35 Area Configuration document” instead)
Z06	Market connection points document	A document specifying connection point and related area where the connection point belongs.
Z07	Rate of exchange document	A document used to distribute Rate of exchange
Z08	Intermediate Confirmation of Aggregate metered data from the Metered Data Aggregator	Intermediate Confirmation of Aggregated Data per Neighbouring Grid from Imbalance Settlement Responsible to Metered Data Aggregator
Z09	Final Confirmation of Aggregate metered data from the Metered Data Aggregator	Final Confirmation of Aggregated Data per Neighbouring Grid from Imbalance Settlement Responsible to Metered Data Aggregator
Z10	Connected Metering Grid Area (MGA) document	Deprecated (use “ B37 Connected Area Document” instead)
Z11	Market Balance Area (MBA) Master Data document	Deprecated (use “ B36 Area Composition document” instead)
Z12	Request change of retailer consumption master data	A document requesting changes to retailer consumption master data, sent from an Entitled Role to the Imbalance Settlement Responsible
Z13	Request change of Resource Object master data	Resource Object master data document where Validity Start and/or Validity End date are changed within the Validity Time Interval (Start date/time inclusive and End date/time exclusive). A document containing master data for a Resource Object
Z14		Deprecated
Z15		Deprecated (use “ A40 DATCR activation” instead)
Z16	Generator Group Relations document	A document containing master data for Generator Group and Generator Relations
Z17	Spot Market Bid Status Report	A document containing a Bid Status from the Spot Market
Z18	Party Relation Master Data Document containing master data changed within the Validity Time Interval	Party Relation Master Data Document containing master data changed within the Validity Time Interval (Start date/time inclusive and End date/time exclusive)
Z19	Party Relation Master Data Document containing all valid master data within the Validity Time Interval	Party Relation Master Data Document containing all valid master data within the Validity Time Interval (Start date/time inclusive and End date/time exclusive)
Z20	Retailer consumption master data document containing master data changed within the Validity Time Interval	Retailer consumption master data document containing master data changed within the Validity Time Interval (Start date/time inclusive and End date/time exclusive)

Z21	Retailer consumption master data document containing all valid master data within the Validity Time Interval	Retailer consumption master data document containing all valid master data within the Validity Time Interval (Start date/time inclusive and End date/time exclusive)
Z22	Resource Object master data document containing master data changed within the Validity Time Interval	Resource Object master data document containing master data changed within the Validity Time Interval (Start date/time inclusive and End date/time exclusive)
Z23	Resource Object master data document containing all valid master data within the Validity Time Interval	Resource Object master data document containing all valid master data within the Validity Time Interval (Start date/time inclusive and End date/time exclusive)
Z24	Request Bilateral Trade Structure Document	A document requesting a new, changed or deleted Bilateral Trade Structure
Z25	Request PX Trade Structure Document	A document requesting a new, changed or deleted PX (Power Exchange) Trade Structure
Z26	Bilateral trade structure master data document containing master data changed within the Validity Time Interval	Bilateral trade structure master data document containing master data changed within the Validity Time Interval (Start date/time inclusive and End date/time exclusive)
Z27	Bilateral trade structure master data document containing all valid master data within the Validity Time Interval	Bilateral trade structure master data document containing all valid master data within the Validity Time Interval (Start date/time inclusive and End date/time exclusive)
Z28	PX trade structure master data document containing master data changed within the Validity Time Interval	PX (Power Exchange) trade structure master data document containing master data changed within the Validity Time Interval (Start date/time inclusive and End date/time exclusive)
Z29	PX trade structure master data document containing all valid master data within the Validity Time Interval	PX (Power Exchange) trade structure master data document containing all valid master data within the Validity Time Interval (Start date/time inclusive and End date/time exclusive)
Z30	Request change of Generator Group (Regulation Object) relations	Used for master data for Resource Objects
Z31	Production Plan Structure – valid for the whole time interval	Used for master data for Resource Objects
Z32	Production Plan Structure – having a start or end within the validity period	Used for master data for Resource Objects
Z33		Deprecated (use B34 instead)
Z34	Market Operator Configuration Document	A document used for sending Market operator calendars.
Z35	ACE OL	A document to provide Area Control Error Open Loop (ACE OL) values
Z36	Power Prognoses	A document to provide power prognoses

2.4 Object aggregation code

	Name	Description
Z01	Generator group	The object being described concerns a group of Reserve objects or Resource objects
Z02	Mutually Regulated Areas (MRA)	The object being described concerns Mutually Regulated Areas (MRA)

2.5 Price category type code

	Name	Description
Z01	Buying	The price for buying commodities in the market.
Z02	Selling	The price for selling commodities in the market.
Z03	Average	Average, i.e. the average price in the market.

2.6 Process type code

	Name	Description
Z01	Frequency controlled reserves market	Processes related to the Frequency controlled reserves market, Primary reserves market
Z02	LFC market	Processes related to the Load Frequency Control market, Secondary reserves market
Z03	Balance regulation market	Processes related to the Balance regulation market, Tertiary reserves market
Z04		Deprecated (Use A58 Reserve option market)
Z05		Deprecated (Use A59 Internal trade reporting instead)
Z06	Total trade	The trade balance of a party at a given time
Z07	Master data	Deprecated (use "A55 Exchange of master data" instead)
Z08	Common Grid Model (CGM) process	
Z09	Coordinated Security Assessment (CSA) process	
Z10	Outage Planning Coordination process	
Z11	Short and Medium Term Adequacy Assessment (SMTA)	
Z12	ACE OL real-time	The process of exchanging real-time ACE OL values
Z13	Corrected real time values	Reporting of real time values after validation and correction.
Z14	Fast Frequency Reserve (FFR) Process	The process of exchanging information regarding the Fast Frequency Reserve (FFR).

2.7 Reason code

	Name	Description
999	Errors not specifically identified	This code is used to identify errors that have not been specifically addressed in the Reason code list. It can be used at any level and refers to the level for which it has been identified.
Z01	Operational	The given unit has a status of operational
Z02	Reduced Operational	The given unit has a status of reduced operational
Z03	Non Operational	The given unit has a status of non operational
Z04	Revision	The given unit is under revision
Z05	Suspended	The given unit is suspended
Z06	Crashed	The given unit is crashed
Z07	Discarded	The given unit is discarded
Z11		Deprecated
Z12		Deprecated
Z13		Deprecated
Z15		Deprecated
Z16		Deprecated
Z17		Deprecated
Z18		Deprecated (use “B17 Price based on preliminary exchange rate” instead)
Z19		Deprecated
Z20	Frequency regulation	The information provided regards a regulation for frequency purpose
Z21	System regulation	The information provided regards a regulation for system purpose
Z22	Supportive power	The object relates to Supportive power
Z23	Special Regulation	The object relates to Special Regulation
Z24	Quarterly adjustments	The object relates to Quarterly adjustments
Z25	Ordinary regulation	The object relates to Ordinary regulation
Z26	Transit triangle	The object relates to Transit triangle
Z27	Transit redispatch	The object relates to Transit redispatch
Z28	Transit SB Loop Long	The object relates to Transit SB Loop Long
Z29	FCR	Frequency Containment Reserve (FCR) is an automatic and momentarily regulation, to adjust the physical balance in the power system.
Z30	FRR-A	Frequency Restoration Reserve - Automatic (FRR-A) is an automatic reserve, activated continuously by the frequency
Z31	FRR-M, Balancing Power	Frequency Restoration Reserve - Manual activated reserves (FRR-M), Balancing Power
Z32	FRR-M, Countertrades	Frequency Restoration Reserve - Manual activated reserves (FRR-M), Countertrades when TSO need to maintain (replace) transfer capacity
Z33	FRR-M, Peak Load Reserve Regulation	Frequency Restoration Reserve - Manual activated reserves (FRR-M), Peak Load Reserve Regulation when no commercial bids are available for balancing.
Z34	FRR-M, Quarter regulation	Frequency Restoration Reserve - Manual activated reserves (FRR-M), Quarter regulation when TSO need transfer of production (usually start 15 min earlier).

Z35	FRR-M, Special Regulation	Frequency Restoration Reserve - Manual activated reserves (FRR-M), Special Regulation where the price is payed as bid and not archive price.
Z36	Hour Change Regulation	In order to reduce problems encountered at the turn of the hour in the Nordic countries or in Finland, Fingrid reserves the right to transfer the planned changes to begin 15 minutes before or after the planned moment
Z37	Power Transaction	Fixed price transaction used for specific purposes outside of ordinary regulation
Z38	TSO Internal Countertrades	The time series concern TSO Internal Countertrades
Z39	Day Ahead Production Adjustment	Energy (production) moved from one hour to another to avoid major changes between hours
Z40	FCR-N	Frequency Containment Reserve, Normal operation (FCR-N)
Z41	FCR-D	Frequency Containment Reserve, Disturbance (FCR-D)
Z42	FCR – N D-1	Frequency Containment Reserve, Normal operation, day minus one
Z43	FCR – N D-2	Frequency Containment Reserve, Normal operation, day minus two
Z44	FCR – N D-1 correction	Frequency Containment Reserve, Normal operation, day minus one, correction
Z45	FCR – N D-2 correction	Frequency Containment Reserve, Normal operation, day minus two, correction
Z46	FCR – D D-1	Frequency Containment Reserve, Disturbance, day minus one
Z47	FCR – D D-2	Frequency Containment Reserve, Disturbance, day minus two
Z48	FCR – D D-1 correction	Frequency Containment Reserve, Disturbance, day minus one, correction
Z49	FCR – D D-2 correction	Frequency Containment Reserve, Disturbance, day minus two, correction
Z50	Supportive power special	The object relates to Supportive power special
Z51	Supportive power disturbance	The object relates to Supportive power disturbance
Z52	Transit SB Loop Short	The object relates to Transit SB Loop Short
Z53	FRR-M, System Regulation	Frequency Restoration Reserve - Manual activated reserves (FRR-M), System Regulation where regulation does not affect the regulation price.
Z54	Activation by AOF (Activation Optimisation Function)	AOF is a function to operate the algorithm applied for the optimisation of the activation of Balancing Energy bids within a Coordinated Balancing Area.
Z55	Manual activation not based on AOF	Manual (locally) activation without use of AOF. AOF is a function to operate the algorithm applied for the optimisation of the activation of Balancing Energy bids within a Coordinated Balancing Area.

2.8 Role code

	Name	Description
Z05		Deprecated (Use A47, Energy Trader instead)
Z06	Regional Security Coordinator	

3 Nordic codes used in Nordic documents

3.1 Bid type code

	Name	Description
Z01	Hourly bid	The details contains hourly bid
Z02	Block bid	The details contains block bid
Z03	Flexible hourly bid	The details contains flexible hourly bid
Z04	Profile block bid	The details contains profile block bid

3.2 Type of Area code

	Name	Description
Z01	Market Balance Area (MBA)	A geographic area consisting of one or more Metering Grid Areas with common market rules for which the settlement responsible party carries out a balance settlement and which has the same price for imbalance. A Market Balance Area may also be defined due to bottlenecks.
Z02	Metering Grid Area (MGA)	A Metering Grid Area is a physical area where consumption, production and exchange can be metered. It is delimited by the placement of meters for period measurement for input to, and withdrawal from the area. It can be used to establish the sum of consumption and production with no period measurement and network losses.

3.3 Production type code

	Name	Description
Z01	Normal	A code indicating that the size of the production unit is normal
Z02	Minor	A code indicating that the size of the production unit is minor

3.4 Production Unit Type code

	Name	Description
Z01	Nuclear	A Production Unit based on Nuclear power
Z02	Hydro	A Production Unit based on Hydro power
Z03	Thermal	A Production Unit based on Thermal power
Z04	Solar	A Production Unit based on Solar power
Z05	Wind	A Production Unit based on Wind power

3.5 MGA Type code

	Name	Description
Z01	Regional	The MGA represent a regional grid
Z02	Only losses	Deprecated
Z03	Industrial	The MGA represent an industrial grid
Z04	Distribution	The MGA represent a distribution grid
Z05	Non-concessional	The MGA represent a non-concessional grid
Z06	Production	The MGA represent the production in a grid
Z07	Transmission (main/central grid)	The MGA represent a transmission (main/central grid)
Z99	Sub-Grid Area	The MGA represent a sub-gid area, i.e. a MGA that is not part of the imbalance settlement, but where a supplier change can take place.

3.6 Settlement method code

	Name	Description
Z01	Flex settled	Consumption or production from small continuously read Accounting Points